



The *Energizer*® Compact 2-in-1 light features innovative Light Fusion Technology® and provides both an area and spot light in a small, versatile design. Unique Light Fusion Technology® delivers vibrant, uniform area illumination for a variety of tasks. With a slim, lightweight design, this innovative solution can easily fit in pockets, drawers and more for easy access to area or directional light.

Lumens	Runtime	Beam Distance	Water Ingress



DESIGN BENEFITS
✓ Compact and lightweight
✓ Integrated lanyard slot
✓ Water resistant

PERFORMANCE BENEFITS
✓ Light Fusion Technology® for vibrant, uniform light
✓ Features Area and Spot modes

LIGHT AND POWER SOURCE
✓ Features LED Technology
✓ Operates on 2 AAA

PRODUCT SPECIFICATIONS
Weight: 59 Grams / 2 Ounces
Dimensions: 119 mm x 49 mm x 18 mm 4.7" x 1.9" x 0.7"

BATTERY SPECIFICATIONS	
Battery Type	ENR Max Alkaline
Battery Size	AAA
Number of Cells	2

BATTERY PERFORMANCE			
Modes	Lumens (lm)	Runtime (h)	Beam Distance (m)
Spot	70	12	30
Area	70	6	---

ELECTRICAL CHARACTERISTICS	
Nominal Power Consumption:	0.69 W Spot 1.08W Area
Batteries:	AAA Energizer E92 3.0V dc
LED Specifications:	LED 3.0V cc / 230 mA Spot LED 3.0V cc / 360 mA Area

DISCLAIMERS
Tested according to ANSI FL1 Standards.
This device complies with part 15 of the FCC Rules.
Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

CERTIFICATES AND COMPLIANCE
EMC, EN62471, FCC

Modes
Spot, Area

OPERATING INSTRUCTIONS

1. Press on/off button to turn on.
2. Press 1x for directional light.
3. Press 2x for area light.

BATTERY CHANGING INSTRUCTIONS

1. Unscrew side panel.
2. Follow diagram on light body for battery orientation.